

CAPACITÀ

ELENCO CONDENSATORI E RESISTORI CHASSIS A. F.

902 RESISTORI

Nomin.	Valore	Tolleranza %	Tensione di prova Volte	Tipo	Nomin.	Valore	Tolleranza %	Watt
C 1	0,025 uf	± 10	300	AF	R 1	0,25 M Ω	± 10	1/4
C 2	0,5 »	± 10	1000	AF	R 2	1 M Ω	± 10	1/2
C 3	0,025 »	± 10	300	AF	R 3	0,0315 M Ω	± 10	1
C 4	0,025 »	± 10	300	AF	R 4	2500 Ω	± 10	1/2
C 5	0,1 »	± 10	1000	AF	R 5	0,01 M Ω	± 10	1/4
C 6	0,1 »	± 10	1500	AF	R 6	0,025 M Ω	± 10	1
C 7	15 pf	± 6	1500	FA2-12	R 7	0,05 M Ω	± 10	1
C 8	4 pf	± 20	1500	FA2-12	R 8	50 Ω	± 10	1/4
C 9	0,025 uf	± 10	300	AF	R 9	0,03 M Ω	± 10	1/2
C 10	0,025 »	± 10	300	AF	R 10	2000 Ω	± 10	1/2
C 11	100 pf	± 5	1500	AF	R 11	2000 Ω	± 10	1/2
C 12	0,025 uf	± 10	300	AF	R 12	1 M Ω	± 10	1/2
C 13	100 pf	± 5	1500	AF	R 13	1 M Ω	± 10	1/2
C 14	1000 pf	± 1	1500	FA2-22P	R 14	2500 Ω	± 10	1/2
C 15	1250 pf	± 1	1500	»	R 15	1 M Ω	± 10	1/2
C 16	410 pf	± 0,5	1500	»	R 16	2 M Ω	± 10	1/2
C 17	45 pf	± 2	1500	»	R 17	0,2 M Ω	± 10	1/4
C 18	15 pf	± 4	1500	FA2-12	R 18	0,1 M Ω	± 10	1/2
C 19	25 pf	± 6	1500	»	R 19	2 M Ω	± 10	1/2
C 20	200 pf	± 1	1500	»	R 20	0,1 M Ω	± 10	1/2
C 21	200 pf	± 1	1500	»	R 21	0,5 M Ω	± 10	1/2
C 22	0,025 uf	± 10	300	AF	R 22	2 M Ω	± 10	1/2
C 23	25 pf	± 4	1500	FA2-12	R 23	2500 Ω	± 10	1/2
C 24	100 pf	± 5	1500	»	R 24	5000 Ω	± 10	1/2
C 25	0,025 uf	± 10	300	AF	R 25	800 Ω	± 10	1/2
C 26	0,01 »	± 10	1500	»	R 26	0,4 M Ω	± 10	1/2
C 27	200 pf	± 1	1500	»	R 27	0,15 M Ω	± 5	1/2
C 28	200 pf	± 1	1500	»	R 28	0,05 M Ω	± 5	1/2
C 29	3,5 pf	± 12	1500	FA2-12	R 29	0,01 M Ω	± 10	1/2
C 30	0,025 uf	± 10	300	AF	R 30	0,1 M Ω	± 10	1/2
C 31	100 pf	± 5	1500	»	R 31	2 M Ω	± 5	1/2
C 32	0,05 uf	± 10	1500	»	R 32	0,04 M Ω	± 10	1/2
C 33	25 »	± 20	1500	Elettrolit	R 33	4 Ω	± 10	4 Filo
C 34	0,1 »	± 10	1000	»	R 34	0,1 M Ω	± 10	1
C 35	8 »	± 20	600	Elettrolit.	R 35	0,05 M Ω	± 10	1/2
C 36	250 pf	± 5	1500	»	R 36	0,2 M Ω	± 10	1/4
C 37	250 pf	± 5	1500	»				
C 38	250 pf	± 5	1500	»				
C 39	0,01 uf	± 10	1500	»				
C 40	0,01 »	± 10	1500	»				
C 41	500 pf	± 10	1500	»				
C 42	1000 pf	± 10	1500	»				
C 43	2000 pf	± 10	3000	»				
C 44	0,02 uf	± 10	1500	»				

RV 1 1 M Ω eso.  
 RV 2 0,5 M Ω » Inv.  
 RT 0,5 M Ω » »

CV 2 }  
 CV 4 } 6,5 ÷ 153,4 pf  
 CV 6 }  
 CV 1+2 }  
 CV 3+4 } 10 ÷ 435 pf  
 CV 5+6 }  
 L 1 ÷ 12 2 ÷ 20 pf

ELENCO CONDENSATORI E RESISTORI CHASSIS B. F.

Nomin.	Valore	Tolleranza %	Tensione di prova Volte	Tipo	Nomin.	Valore	Tolleranza %	Watt
C 50	0,025 uf	± 10	1500	»	R 40	1000 Ω	± 5	1/2
C 51	0,025 »	± 10	1500	»	R 41	1000 Ω	± 5	1/2
C 52	5000 pf	± 10	3000	»	R 42	0,1 M Ω	± 10	1/2
C 53	5000 pf	± 10	1500	»	R 43	0,1 M Ω	± 10	1/2
C 54	500 pf	± 10	1500	»	R 44	25 Ω	± 10	1/2
C 55	200 uf	± 20	30	Elettrolit.	R 45	0,5 M Ω	± 10	1/2
C 56	500 pf	± 10	1500	»	R 46	0,5 M Ω	± 10	1/2
C 57	8 uf	± 20	600	Elettrolit.	R 47	0,1 M Ω	± 5	1
C 58	8 »	± 20	600	»	R 48	1000 Ω	± 10	1/4
C 59	8 »	± 20	600	»	R 49	80 Ω	± 10	1
C 60	8 »	± 20	600	»	R 50	1000 Ω	± 10	1/4
C 61	16 »	± 20	450	»	R 51	0,1 M Ω	± 5	1
C 62	16 »	± 20	450	»	R 52	8000 Ω	± 5	2
					R 53	1000 Ω	± 5	Eccit. all.
					R 54	6300 Ω	± 10	6 Filo