



	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	A	B	C	D	E	F
C 2	●	○	○	○	○	○	○	○	○	○	○	○	○	○	○	○	○	○	○	○	○
C 1	○	●	○	○	○	○	○	○	○	○	○	○	○	○	○	○	○	○	○	○	○
M	○	○	○	○	○	○	○	○	○	○	○	○	○	○	○	○	○	○	○	○	○
F.	○	○	○	○	○	○	○	○	○	○	○	○	○	○	○	○	○	○	○	○	○
																●	●	○	○	○	○
																●	○	○	○	○	○
																●	○	○	○	○	○
																●	○	○	○	○	○
																●	○	○	○	○	○
																●	○	○	○	○	○

C 1	2.000	pf
C 2	50	pf
C 3	100	pf
C 4	75	pf
C 5	200	pf
C 6	50	pf
C 7	75	pf
C 8	4.000	pf
C 9	300	pf
C 10	200	pf
C 11	200	pf
C 12	200	pf
C 13	50.000	pf
C 14	25	pf
C 15	100.000	pf
C 16	10.000	pf
C 17	200	pf
C 18	25.000	pf
C 19	200	pf
C 20	200	pf
C 21	1.000	pf
C 22	25.000	pf
C 23	10.000	pf
C 24	250	pf
C 25	5.000	pf
C 26	10.000	pf
C 27	50+50 M	pf
C 28	50	pf
C 29	Tutto	
C 30	15.000	pf
C 31	25.000	pf
C 32	25.000	pf
C 33	100 M	pf
C 34	5.000	pf
C 35	5.000	pf
C 36	50 M	pf
C 37	2.000	pf
C 38	5.000	pf
C 39	5.000	pf
R 1	1 M	Ω
R 2	47 K	Ω
R 3	47 K	Ω
R 4	22 K	Ω
R 5	0.47 M	Ω
R 6	1 M	Ω
R 7	1 M	Ω
R 8	33 K	Ω
R 9	4700	Ω
R 10	470	Ω
R 11	2.2 M	Ω
R 12	47 K	Ω
R 13	47 K	Ω
R 14	27 K	Ω
R 15	10 K	Ω
R 16	39 K	Ω
R 17	22 K	Ω
R 18	22 K	Ω
R 19	120 K	Ω
R 20	82 K	Ω
R 21	220	Ω
R 22	330	Ω
R 23	330	Ω
R 24	5600	Ω
R 25	5600	Ω
R 26	130	Ω
R 27	22	Ω
R 28	330	Ω
R 29	330	Ω
R 30	5600	Ω
R 31	5600	Ω
R 32	130	Ω
R 33	220	Ω

FIMI S.A. - PHONOLA - Modd. 639 e 640. Onde medie da 183 a 575 metri. Onde corte da 27,3 a 80 metri e da 15,8 a 28 metri. Media frequenza 470 kc/s. Consumo 80 watt. Potenza indistorta 10 watt. Montaggio della cordina come per il mod. 5532 F. Disposizione dei compensatori R. F. e bobine come per il mod. 5576.