



NOTE- 9A ALTO  
9B TREBLE  
9C VOICE  
9D NORMAL  
9E LOW BASS  
9F BASS

SPEAKER	MODEL
49-179-8*	7 S-323
49-251-10*	7 S-342
49-251-10*	7 S-343
49-208-10*	7 S-363
49-249-12*	7 S-366
49-266-12*	7 S-364

DWG NO	PART NO	DESCRIPTION	DWG NO	PART NO	DESCRIPTION	DWG NO	PART NO	DESCRIPTION	DWG NO	PART NO	DESCRIPTION
C-1	22-717	TWP RANGE VAR COND	C-7	22-435	.02 MFD	600V	R-13	63-825	VOLUME CONTROL	14	1
C-2	22-389	50 MFD	C-8	22-218	.03 MFD	200V	R-14	63-843	10 M OHM	14	2
C-3	22-182	200 MFD	C-9	22-492	.02 MFD	600V	R-15	63-843	1 MEG OHM MOUNTED IN TUNING TUBE BASE	14	3
C-4	22-127	.25 MFD	C-24	22-718	.12 MFD ELECTROLYTIC	450V					
C-5	22-170	.1 MFD	C-23	22-719	.16 MFD ELECTROLYTIC	350V					
C-6	22-212	.05 MFD									
C-7	22-210	.05 MFD									
C-8	22-519	TRIMMER COND									
C-9	22-340	COMPENSATING COND									
C-10	22-708	DUAL FIXED INDUORP	R-1	63-621	39 OHM	1/2 W	3	5-825	ORC COIL & SHIELD 100MM		
C-11	22-358	.002 MFD	R-2	63-582	33 M OHM	1/2 W	4	20-196	COMPENSATING COIL		
C-12	22-327	.02 MFD	R-3	63-597	470 M OHM	1/2 W	5	70-156	WAVE TRAP		
C-13	22-182	.0025 MFD	R-4	63-861	47 M OHM	1/2 W	6	85-151	BAND SELECTOR SWITCH		
C-14	22-470	.0015 MFD	R-5	63-640	10 M OHM	1/2 W	7	85-836	1ST I.F. TRANS RANGEAMP		
C-15	22-185	.01 MFD	R-7	63-271	1 MEG OHM	1/2 W	8	85-837	2ND I.F. TRANS RANGEAMP		
C-16	22-187	.005 MFD	R-8	63-555	220 M OHM	1/2 W	9	1-6224	TUNE CONTROL SW. 400MM		
C-17	22-450	.006 MFD	R-9	61-296	250 M OHM	1/2 W	10	85-932	AUTOMATIC TUNING SWITCH		
C-18	22-826	.003 MFD	R-10	63-883	100 M OHM	1/2 W	11	85-225	POWER TRANS 10T 50-60 ~		
C-19	22-190	.1 MFD	R-11	63-591	22 M OHM	1/2 W	13	85-578	POWER TRANS ILLUMINATOR 25 ~		
C-20	22-444	.006 MFD	R-12	63-884	3 SECTION CAMDOWN	1/2 W	14	100-16	PILOT LIGHT 25.5 - 83V SPEAKER TAPING		

I.F. FREQUENCY 455 K.C.  
7 TUBE SUPERHETERODYNE  
CHASSIS No 5714-A.C. 3-BAND  
ZENITH RADIO CORPORATION

Chassis No. 5714

NOTE-TRIMMERS "K-K & N"  
MOUNTED ON BAKELITE  
3202-PART 1112-312