



Rifer.:	Schema	Descrizione materiali	Rifer.:	Schema	Descrizione materiali	Rifer.:	Schema	Descrizione materiali	Rifer.:	Schema	Descrizione materiali	Rifer.:	Schema	Descrizione materiali
R 1	Res. 0,2 W	10 K Ω \pm 5 %	R 16	Res. 0,2 W	2,2 K Ω \pm 10 %	C 4	Cond.	0,01 μ F	C 18	Cond.	2000 pF \pm 10 %	Tr 1	Transistore	OC44
R 2	"	39 "	R 17	"	10 " \pm 5 %	C 5	"	variabile	C 19	"	0,01 μ F	Tr 2	"	OC45
R 3	"	1,5 "	R 18	"	33 "	C 6	"	"	C 20	"	12 " 3 VL	Tr 3	"	OC45
R 4	"	1,5 " \pm 10 %	R 19	"	560 Ω "	C 7	"	3000 pF \pm 5 %	C 21	"	80 " 6 VL			
R 5	"	470 Ω "	R 20	"	560 " "	C 8	"	0,04 μ F	C 22	"	50 " 12,5 VL	D 1	Diodo al germanio	OA174
R 6	"	680 " \pm 5 %	R 21	"	150 K Ω \pm 10 %	C 9	"	12 " 3VL	C 23	"	0,01 "			
R 7	"	680 " \pm 10 %	R 22	"	470 Ω "	C 10	"	0,04 "				Tr 4	Transistore	OC71
R 8	"	10 K Ω \pm 5 %	R 23	Potenz.	3 K Ω	C 11	"	41 pF \pm 2,5 %	L 1	Antenna ferrite		Tr 5	"	OC72
R 9	"	47 " "	R 24	Res. 0,2 W	100 Ω \pm 5 %	C 12	Cond.	1000 " \pm 5 %	L 2	Bobine oscill. OM		Tr 6	"	OC72
R 10	"	1100 Ω \pm 10 %	R 25	Resist.	130 Ω NTC 10 %	C 13	"	2000 " \pm 10 %						
R 11	"	680 " \pm 5 %	R 26	Res.	3,3 Ω \pm 10 %	C 14	"	0,04 μ F	T 1	Trasform. I MF				
R 12	"	680 " \pm 10 %				C 15	"	0,04 "	T 2	" II MF				
R 13	"	10 K Ω "	C 1	Cond.	variabile	C 16	"	25 pF \pm 1 %	T 3	" III MF				
R 14	"	100 " "	C 2	"	"	C 17	Cond.	3000 pF \pm 5 %	T 4	" entrata				
R 18	Potenz.	10 K Ω	C 3	"	5000 pF				T 5	" uscita				

« CGE »

RADIORICEVITORE A 6 TRANSISTORI

Mod. 0596

